

BAROLI 02

Battery Powered Digital Pressure Gauge

Stainless Steel Sensor

class 0.1



Digital Pressure Gauge

BAROLI 02

Nominal pressure

from 0 ... 100 mbar
up to 0 ... 600 bar

Special characteristics

- ▶ rotatable housing
- ▶ 2-line LC display
4.5-digit 7-segment display
6-digit 14-segment additional display

Functions

- ▶ min / max function with
reset function
- ▶ offset and end point calibration
- ▶ setting the pressure unit
(bar, mbar, psi, InHg, cmHg, mmHg,
hPa, kPa, MPa, mH₂O)
- ▶ switch-off automatic

CE

The battery-powered digital pressure gauge *BAROLI 02* enables a local displaying of values, satisfying the highest demands for accuracy and long-term stability.

The pressure gauge may be applied in all media compatible with the stainless steel used; it shows an excellent robustness and a high overpressure protection.

The *BAROLI 02* display housing is rotatable, thus ensuring an easy reading even under unfavorable mounting conditions.

Additional functions as changing the unit, displaying min / max values, calibrating of offset and the span, as well as configuring the automatic switching-off complete the profile.

Preferred areas of use are



Plant and Machine Engineering
Pneumatics / Hydraulics
Measurement Technology
Calibration and Test Purposes



Laboratory Techniques



Environmental Engineering
(water – sewage – recycling)

Input pressure ranges											
Nominal pressure gauge / abs. [bar]	0.10	0.16	0.25	0.40	0.60	1	1.6	2.5	4	6	
Overpressure [bar]	0.5	1	1	2	5	5	10	10	20	40	
Burst pressure [bar]	1.5	1.5	1.5	3	7.5	7.5	15	15	25	50	
Nominal pressure gauge / abs. [bar]	10	16	25	40	60	100	160	250	400	600	
Overpressure [bar]	40	80	80	105	210	210	600	1050	1050	1250	
Burst pressure [bar]	50	120	120	210	420	420	1000	1250	1250	1250	
Vacuum pressure	-1 ... 0 bar, overpressure: 5 bar, burst pressure: 7.5 bar other vacuum ranges on request										
Vacuum resistance	$P_N \geq 1$ bar: unlimited vacuum resistance $P_N < 1$ bar: on request										

Performance			
Accuracy	nominal pressure ≥ 0.4 bar: $\leq \pm 0.125$ % FSO BFSL nominal pressure: < 0.4 bar: $\leq \pm 0.25$ % FSO BFSL		
Measuring rate	5/sec		
Long term stability	$\leq \pm 0.1$ % FSO / year		
Thermal effects (Offset and Span)			
Nominal pressure P_N [bar]	-1 ... 0	≤ 0.40	> 0.40
Tolerance band [% FS]	$\leq \pm 0.75$	$\leq \pm 1$	$\leq \pm 0.75$
in compensated range [°C]	-20 ... 85 °C	0 ... 70 °C	-20 ... 85 °C
Permissible temperatures			
Permissible temperatures	medium: -20 ... 85 °C	environment: -20 ... 70 °C	storage: -30 ... 80 °C
Mechanical stability			
Vibration	5 g RMS (25 ... 2000 Hz)	according to DIN EN 60068-2-6	
Shock	100 g / 1 msec	according to DIN EN 60068-2-27	
Materials			
Pressure port / Housing	stainless steel 1.4404 (316 L)		
Display housing	PA 6.6, polycarbonate		
Seals (media wetted)	FKM		
Diaphragm	stainless steel 1.4435 (316 L)		
Media wetted parts	pressure port, seals, diaphragm		
Miscellaneous			
Display	LC display, visible range 40 x 30 mm; 4.5-digit 7-segment-display, digit height 11 mm, range of indication ± 19999 ; 6-digit 14-segment additional display, digit height 7.5 mm		
Electromagnetic compatibility	emission and immunity according to EN 61326		
Supply	3.6 V Lithium battery; 2 piece (type 1/2 AA)		
Data storage	EEPROM (non-volatile)		
Ingress protection	IP 65		
Installation position	any ¹		
Weight	approx. 300 g		
AD-converter solution	14 Bit		
Operational life of battery	standby mode: approx. 5 years		
mech. operational life	$> 100 \times 10^6$ pressure cycles		
CE-conformity	EMC Directive: 2004/108/EG		Pressure Equipment Directive: 97/23/EG (Modul A) ²

¹ The digital pressure gauge is calibrated in a vertical position with the pressure connection down. If this position is changed on installation there can be slight deviations in the zero point for devices with stainless steel sensor and pressure range $P_N \leq 1$ bar.

² This directive is only valid for devices with maximum permissible overpressure > 200 bar.

Dimensions (in mm)			

Website

www.SensorsONE.co.uk

Email

enquiries [at] SensorsONE.co.uk

QR Code

Save the SensorsONE website address to your mobile smartphone by scanning this QR code

